

FLASHER



KEY FEATURES

- 2 Channels
- High Current Low Side Mosfet Outputs
- Powered by either 12 or 24V
- Factory Programmable
- Ready for Immediate Operation

Flasher is an electronic device with two independent low side output signals which can control for e.g flash lamps mounted on the front, rear or on the vehicle sides, warning for open steps etc.

The flasher can be programmed to different flashing user patterns.

PRODUCT CODE

FLASHER 2N Flasher 2x Output GND, 1A, 10-30V DwC, fact. programmable

SPECIFICATIONS

POWER	
Supply Voltage	8-30 V DC
Current	0.1 A maximum, no outputs active
Electrical Protection	reverse polarity
I/O AND INTERFACE	
Digital Output	1 x CAN
OUT1	negative switching (low-side), max. 2 A
OUT2	negative switching (low-side), max. 2 A
Loads	inductive, resistive
ENVIROMENT	
IP Class (IEC259)	IP20
Temperature Range	storage from -40° to +85°C operating from -40° to +85°C
ENCLOSURE	
Housing Material	ABS
Mounting	with 1 screw
Connector	faston 2.8 x 0.8
SIZE AND WEIGHT	
W x H x D	45 x45 x 18 mm without connector
Weight	0.1 kg

DIMENSIONS

